



LED driver with integrated single LED monitoring for detection of defective LED in case of short-circuit or open circuit. Continuous monitoring of LED luminaires during maintained operation. Free configuration of each luminaire according to the requested operation mode in maintained, non-maintained or switched-maintained operation without the need of an additional data line. Each luminaire is switchable and dimmable via the control unit of the system. Including timer function to switch off or dim luminaires in battery mode to reduce the required lighting level (acc. to EN 12193) or in buildings with different rated duration times. Addressing with fixed ID without requirement of manual adjustment. High functional reliability due to the fulfillment of international standards for safety and operation, electromagnetic compatibility and immunity to interference. LED driver with active power factor correction (PFC) to reduce the reactive power in mains operation. For connection to FUSION central battery- or emergency power (NEA) systems.

Auswechselbares Betriebsgerät zur vereinfachten Wartung und Instandhaltung.

## Technical details

<b>Material</b>	polycarbonate
<b>Protection category</b>	IP20
<b>Permitted temperature range</b>	-15...+45 °C
<b>Nominal voltage DC</b>	176 - 264 V

## **FLD-Supply 230/320 SK II ext.**

Art. no.: 101445226

<b>Nominal voltage AC</b>	230V AC/DC $\pm 10\%$ 50/60 Hz
<b>Input terminal</b>	max. 2.5 mm <sup>2</sup> single-core or max. 1.5mm <sup>2</sup> multi-core with ferrule
<b>Output current</b>	320 mA
<b>Dim.</b>	Length x Width x Height: 185 mm x 49 mm x 61 mm
<b>max connection capacity</b>	8 W
<b>Type of current</b>	constant current