

230V

J/SV

SN/A 8627 Downlights

For connection to JOKER-central battery systems



Combined wall or ceiling luminaire for general and safety lighting.

Technical data


Material:	polycarbonate
Illuminant:	12 x 0,3W + 70 x 0,3W LED-module
Luminous flux:	461 lm
Nominal voltage AC:	230V ±10% 50/60 Hz
Nominal voltage DC:	176 - 264 V
Nominal current AC:	37 mA
Nominal current DC:	36 mA

Apparent power:	8,6 VA
Effective power:	6,5 W
Inrush current:	8 A / 50 µs
Protection class:	I
Input terminals:	2.5mm ² feed through wiring
Temperature ta:	-15...+30 °C
Impact resistance:	IK06

Technical data (General lighting)

Nominal voltage AC:	230V AC/DC ±10% 50/60 Hz
Apparent power:	33,0 VA
Leistung (Allgemeinlicht):	32,0 W

Light colour:	3000 K, 4000 K
Luminous flux:	3028 lm
inrush current:	18 A / 216 µs



Ceiling mounting: Minimum illumination 1.0lx (middle of escape route), Maintenance factor 0.8

	Distance to middle of escape route				
	1.0m		2.0m		
2.0	3.2	8.1	3.5	9.1	
2.5	3.1	8.1	3.5	9.4	
3.0	3.0	8.1	3.5	9.5	

Wall mounting: Minimum illumination 1.0lx (middle of escape route), Maintenance factor 0.8

	Distance to middle of escape route				
	1.0m		2.0m		
2.0	3.2	8.1	3.5	9.1	
2.5	3.1	8.1	3.5	9.4	
3.0	3.0	8.1	3.5	9.5	


Articles**SN/A 8627 LED J/SV**

Colors	RAL 9010
Art. no.	101308921

wall or ceiling mounting

Light colour: 3000 K

Protection category: IP40


**SN/A 8627 LED J/SV**

Colors	RAL 9010
Art. no.	101308517

wall or ceiling mounting

Light colour: 4000 K

Protection category: IP40



Name	Accessories	Art. no.
Cover 8627	Ersatzteil	050308
J - ET 7 SV - max. 12V DC,650mA const	Ersatzteil	101420772
LED driver replacement SN 8627	Ersatzteil	101861417
LED replacement kit 3K AV/SV SN 8627	Ersatzteil	101861518
LED replacement kit 4K AV/SV SN 8627	Ersatzteil	101861619
motion detector-unit smartSWITCH	optional	101435223